

Finite-time chaos synchronization of the delay hyperchaotic Lü system with disturbance

Yan Zhou, Juanjuan Huang, Zuolei Wang*, Xuerong Shi

School of Mathematics and Statistics, Yancheng Teachers University, Yancheng, 224002, China

(Received January 04 2019, accepted May 29 2019)

Abstract. In this paper, the dynamics and the finite-time synchronization of the delay hyperchaotic Lü system with disturbance are discussed. Based on the finite-time stability theory, a control law is put forward to realize finite-time chaos synchronization of the delay hyperchaotic Lü system with disturbance. Finally, numerical simulation results are provided to demonstrate the effectiveness and robustness of the proposed scheme.

Keywords: Chaos, delay system, disturbance, finite-time synchronization

1. Introduction

Chaos synchronization has attracted due attention of many researchers since the seminal work of Pecora and Carroll [1]. From then on, chaos synchronization has been developed in an extensive and intensive manner due to its potential application in varied fields, like secure communication [2, 3], complex networks [4-7], biotic science [8-13] and so on [14-26].

Nowadays, most of the major findings about chaos control and synchronization are derived based on the asymptotic stability of the chaotic systems. In fact, it is more valuable to control or synchronize chaotic systems as soon as possible. To obtain faster convergence, the finite-time control approach is an effective technique. In addition, the finite-time techniques have been demonstrated to show better robustness and disturbance rejection properties than those of asymptotic methods [27-37]. Therefore, the finite-time chaos control and synchronization have gained a great deal of attention over the past few decades. Mohammad et al. brought in an adaptive control scheme for chaos suppression of non-autonomous chaotic rotational machine systems with fully unknown parameters in finite time [38]. Gao et al. proposed a zero error system algorithm on the basis of automatic control theory and finite-time control principle [39]. Wang et al. employed a nonlinear controller to control chaos in a BLDCM system within the frameworks of the finite-time stability theory and the Lyapunov stability theory [40]. Several finite-time synchronization methods have been put forward in [41-43].

On the other hand, it is difficult to know the external disturbance always occurs in system. Thus, the chaos control and synchronization of chaotic system in the presence of external disturbance are effectively crucial in practical applications.

The present paper intends to present a controller with a view to realizing finite-time synchronization of delay hyperchaotic Lü system with disturbance. The controller is robust and simple to be constructed. Numerical simulations are presented to reveal the effectiveness and robustness of the proposed scheme.

The rest of the paper is organized as follows. Section 2 offers a brief account of the preliminary definitions and lemmas. Section 3 investigates the dynamics of delay hyperchaotic Lü system with disturbance and proposes the finite-time controllers. Simulation results are presented in Section 4 and the conclusion of the whole paper is drawn in Section 5.

2. Preliminary definitions and lemmas

By finite-time synchronization, it is meant that the state of the slave system can track that of the master system after a finite-time.

Definition 1. Consider the following two chaotic systems:

$$\begin{aligned}\dot{x}_t &= f(x_t), \\ \dot{x}_s &= h(x_t, x_s),\end{aligned}\tag{1}$$

* Corresponding author. E-mail address: wangzuolei1971@163.com.

where x_t, x_s are two n -dimensional state vectors. The subscripts 't' and 's' stand for the master and slave systems, respectively. $f: R^n \rightarrow R^n$ and $h: R^n \rightarrow R^n$ are vector-valued functions. If there exists a constant $T > 0$, such that

$$\lim_{t \rightarrow T} \|x_t - x_s\| = 0,$$

and $\|x_t - x_s\| \equiv 0$, if $t \geq T$, then synchronization of the system (1) is achieved in a finite-time.

Lemma 1 [32]. Assume that a continuous, positive-definite function $V(t)$ satisfies differential inequality

$$\dot{V}(t) \leq -cV^\eta(t), \forall t \geq t_0, V(t_0) \geq 0, \quad (2)$$

where $c > 0, 0 < \eta < 1$ are constants, then, for any given t_0 , $V(t)$ satisfies inequality

$$V^{1-\eta}(t) \leq V^{1-\eta}(t_0) - c(1-\eta)(t-t_0), t_0 \leq t \leq t_1, \quad (3)$$

and

$$V(t) \equiv 0, \forall t \geq t_1,$$

with t_1 given by

$$t_1 = t_0 + \frac{V^{1-\eta}(t_0)}{c(1-\eta)}. \quad (4)$$

Proof. Consider differential equation

$$\dot{X}(t) = -cX^\eta(t), X(t_0) = V(t_0), \quad (5)$$

although differential equation (6) does not satisfy the global Lipschitz condition, the unique solution of Eq.(6) can be found as

$$X^{1-\eta}(t) = X^{1-\eta}(t_0) - c(1-\eta)(t-t_0). \quad (6)$$

Therefore, from the comparison Lemma, one obtains

$$V^{1-\eta}(t) \leq V^{1-\eta}(t_0) - c(1-\eta)(t-t_0), t_0 \leq t \leq t_1, \quad (7)$$

and

$$V(t) \equiv 0, \forall t \geq t_1.$$

with t_1 given in (5).

Lemma 2 [34]. If $\alpha > \left(\frac{2}{3}\right)^{\frac{2}{3}}$, it can be gotten that

$$\left(\alpha|x_1| + \frac{1}{2}x_2^2\right)^{\frac{3}{2}} + x_1x_2 \geq 0, \quad (8)$$

where x_1 and x_2 are any real numbers.

Corollary 1 [34]. If $\alpha > \left(\frac{2}{3}\right)^{\frac{2}{3}}$, it can be obtained that

$$|x_1x_2| \leq \left(\alpha|x_1| + \frac{1}{2}x_2^2\right)^{\frac{3}{2}}, \quad (9)$$

where x_1 and x_2 are any real numbers.

Lemma 3 [44]. Let $0 < c < 1$. Then for positive real numbers a and b , the following inequality holds

$$(a+b)^c < a^c + b^c. \quad (10)$$

3. Main results

A chaotic system is of tremendous sensitivity to disturbance. In actual situation, the system is disturbed and cannot be exactly predicted. These uncertainties will in turn destroy the synchronization and even break it. Therefore, it is of great importance and necessity to study the synchronization of systems with disturbance. In this section, the dynamic behaviors of the delay hyperchaotic Lü system is to be explored, and the finite-time synchronization of the delay hyperchaotic Lü systems will be discussed as well.

3.1 Dynamics of delay hyperchaotic Lü system with disturbance

Delay hyperchaotic Lü system with disturbance is considered as

$$\begin{aligned} \dot{x}_1 &= a(x_2 - x_1), \\ \dot{x}_2 &= cx_2 - x_1x_3 + x_4(t-\tau) + Ax_2 \sin(\omega t), \\ \dot{x}_3 &= x_1x_2 - bx_3, \\ \dot{x}_4 &= -kx_1 - dx_2. \end{aligned} \quad (11)$$